

# 100W JSK100双路隔离地系列



交流输入范围通过开关置换  
具有过压, 过流及短路保护  
自然风冷  
100%满载老化测试  
外型尺寸为200\*98\*40 (mm)  
内置间距9.5mm端子

<b>JSK100-A2D0515G</b>	<b>JSK100-A2D0512G2</b>	<b>JSK100-A2D0505G</b>	<b>JSK100-A2D12G</b>
<b>5V/3A 15V/3A</b>	<b>5V/12AG1 12V/3AG2</b>	<b>5V/10AG1 5V/10AG2</b>	<b>12V/6A -12V/3A</b>
<b>JSK100-A2D1206G</b>	<b>JSK100-A2D1224G</b>	<b>JSK100-A2D1205G</b>	<b>JSK100-A2D30G</b>
<b>6V/2A -12V/5A</b>	<b>12V/5AG1 24V/2AG2</b>	<b>12V/8AG1 5V/2AG2</b>	<b>30V/2AG1 30V/2AG2</b>
<b>JSK100-A2D1209G</b>	<b>JSK100-A2D2805G</b>	<b>JSK100-A2D2812G</b>	<b>JSK100-A2D2409G</b>
<b>12V/10AG1 9V/1AG2</b>	<b>28V/4A 5V/1A</b>	<b>28V/2AG1 12V/2AG2</b>	<b>24V/5AG1 5V/3.5AG2</b>
<b>JSK100-A2D2424G</b>	<b>JSK100-A2D2409G</b>	<b>JSK100-A2D2405G</b>	<b>JSK100-A2D2405G</b>
<b>24V/2AG1 24V/2AG2</b>	<b>24V/3A 9V/1.5A</b>	<b>24V/4AG1 5V/1AG2</b>	<b>24V/4.5A 5V/3A</b>
<b>JSK100-A2D2412G</b>	<b>JSK100-A2D2405G</b>	<b>JSK100-A2D2412G</b>	<b>JSK100-A2D2405G</b>
<b>24V/5AG1 12V/1AG2</b>	<b>24V/3AG1 5V/2AG2</b>	<b>24V/3AG1 12V/2AG2</b>	<b>24V/5AG1 5V/1AG2</b>

输入电压范围: ..... 88~132VAC/176~264VAC (开关选择) 248~370VDC

输入电流: ..... 1.9A/115VAC 0.9A/230VAC

冲击电流: ..... 冷启动电流30A/115VCA 60A/230VAC

漏电流: ..... <2mA/240VAC

直流电压可调范围: ..... 额定输出电压的±10%

输出过载保护: ..... 105%~135%切断输出, 重启后恢复

输出过电压保护: ..... 115%~135%

启动、上升、保持时间: ... 200ms 50ms 20ms

耐压: ..... I/P-O/P:1.5KVAC I/P-FG:1.5KVAC O/P-FG:0.5KVAC

工作温度、湿度: ..... -10℃~+60℃, 20%~90%RH, 无冷凝

储存温度、湿度: ..... -20℃~+85℃, 10%~95%RH

耐震动: ..... 10~500Hz, 2G 10分钟/周期, X、Y、Z轴各60分钟

安全标准: ..... 根据GB4943、UL60950、EN60950设计

电磁兼容: ..... 根据GB9254、EN55022 A级设计

# 结构尺寸

